POWER SUPPLY MONITOR DEVICES

EML22/UML23N

●Features

1) Packaging Zener diode and small-signal amplifier transistor

2) Using outside connection able to use Power supply monitor device

3) When use Power supply monitor device, Temparature drift characteristics of detect voltage is about 150 ppm/ºC.

●Applications

Protection of over load of power supply.

●Dimensions (Unit : mm)

EMT6



MARKING : "L22"(EMT6)

UMT6
(SC-88)
<SOT-363>



MARKING : "L23"(UMT6)

●Packaging specifications and Marking

Type	EML22	UML23N
Package	EMT6	UMT6
Marking	L22	L23
Code	T2R	TR
Basic ordering unit (pieces)	8000	3000

●Absolute maximum ratings (Ta=25°C)

Tr

Parameter	Symbol	Limits	Unit
Collector-base voltage	V_{CBO}	60	V
Collector-emitter voltage	V_{CEO}	50	V
Emitter-base voltage	V_{EBO}	7	V
Collector current	I_C	150	mA
Power dissipation	P_D*1	120	mW

Di

Parameter	Symbol	Limits	Unit
Power dissipation	P_D*1	120	mW

Tr and Di

Parameter	Symbol	Limits	Unit
Power dissipation	P_D*1	150	mW
Junction temperature	Tj	150	°C
Range of storage temperature	Tstg	−55 to +150	°C

*1 Mounted on reference land.

●Internal circuit



●**Electrical characteristics** (Ta = 25°C)

Tr

Parameter	Symbol	Min.	Typ.	Max.	Unit	Conditions
Collector-emitter brekdown voltage	BV_{CEO}	50	—	—	V	I_C=1mA
Collector-base breakdown voltage	BV_{CBO}	60	—	—	V	I_C=50μA
Emitter-base breakdown voltage	BV_{EBO}	7	—	—	V	I_E=50μA
Collector cut-off current	I_{CBO}	—	—	100	nA	V_{CB}=60V
Emitter cut-off current	I_{EBO}	—	—	100	nA	V_{EB}=7V
Collector-emitter saturation voltage	$V_{CE(sat)}$	—	—	400	mV	I_C/I_B=50mA/5mA
DC current gain	h_{FE}	120	—	390	—	V_{CE}=6V,I_C=1mA
Transition frequency	f_T	—	180	—	MHz	V_{CE}=12V,I_E=−2mA, f=100MHz
Output capacitance	C_{ob}	—	2	—	pF	V_{CB}=12V,I_E=0A, f=1MHz

Di

Parameter	Symbol	Min.	Typ.	Max.	Unit	Conditions
Zener voltage	V_Z	6.58	6.80	7.00	V	I_Z=5mA
Reverse current	I_R	—	—	0.5	mA	V_R=3.5V

●Electrical characteristic curves

<Tr>



Fig. 1 GROUNDED EMITTER PROPAGATION CHARACTERISTICS



Fig. 2 GROUNDED EMITTER OUTPUT CHARACTERISTICS (Ⅰ)



Fig. 3 GROUNDED EMITTER OUTPUT CHARACTERISTICS (Ⅱ)



Fig.4 DC CURRENT GAIN vs. COLLECTOR CURRENT CHARACTERISTICS (Ⅰ)



Fig. 5 DC CURRENT GAIN vs. COLLECTOR CURRENT CHARACTERISTICS (Ⅱ)



Fig. 6 COLLECTOR SATURATION VOLTAGE vs. COLLECTOR CURRENT CHARACTERISTICS(Ⅰ)



Fig. 7 COLLECTOR SATURATION VOLTAGE vs. COLLECTOR CURRENT CHARACTERISTICS(Ⅱ)



Fig. 8 COLLECTOR SATURATION VOLTAGE vs. COLLECTOR CURRENT CHARACTERISTICS(Ⅲ)



Fig.9 Gain bandwidth product vs. emitter current



Fig.10 Collector output capacitance vs. collector-base voltage
Emitter input capacitance vs. emitter-base voltage



Fig.11 Base-collector time constant vs. emitter current

<Di>







<Tr+Di>





Fig.16 Reference Voltage vs Temperature Characteristics

●Measurement circuits



Fig 17 Reference Voltage vs Temperature Characteristics Mesurement CIrcuit

Notes

No copying or reproduction of this document, in part or in whole, is permitted without the consent of ROHM Co.,Ltd.

The content specified herein is subject to change for improvement without notice.

The content specified herein is for the purpose of introducing ROHM's products (hereinafter "Products"). If you wish to use any such Product, please be sure to refer to the specifications, which can be obtained from ROHM upon request.

Examples of application circuits, circuit constants and any other information contained herein illustrate the standard usage and operations of the Products. The peripheral conditions must be taken into account when designing circuits for mass production.

Great care was taken in ensuring the accuracy of the information specified in this document. However, should you incur any damage arising from any inaccuracy or misprint of such information, ROHM shall bear no responsibility for such damage.

The technical information specified herein is intended only to show the typical functions of and examples of application circuits for the Products. ROHM does not grant you, explicitly or implicitly, any license to use or exercise intellectual property or other rights held by ROHM and other parties. ROHM shall bear no responsibility whatsoever for any dispute arising from the use of such technical information.

The Products specified in this document are intended to be used with general-use electronic equipment or devices (such as audio visual equipment, office-automation equipment, communication devices, electronic appliances and amusement devices).

The Products specified in this document are not designed to be radiation tolerant.

While ROHM always makes efforts to enhance the quality and reliability of its Products, a Product may fail or malfunction for a variety of reasons.

Please be sure to implement in your equipment using the Products safety measures to guard against the possibility of physical injury, fire or any other damage caused in the event of the failure of any Product, such as derating, redundancy, fire control and fail-safe designs. ROHM shall bear no responsibility whatsoever for your use of any Product outside of the prescribed scope or not in accordance with the instruction manual.

The Products are not designed or manufactured to be used with any equipment, device or system which requires an extremely high level of reliability the failure or malfunction of which may result in a direct threat to human life or create a risk of human injury (such as a medical instrument, transportation equipment, aerospace machinery, nuclear-reactor controller, fuel-controller or other safety device). ROHM shall bear no responsibility in any way for use of any of the Products for the above special purposes. If a Product is intended to be used for any such special purpose, please contact a ROHM sales representative before purchasing.

If you intend to export or ship overseas any Product or technology specified herein that may be controlled under the Foreign Exchange and the Foreign Trade Law, you will be required to obtain a license or permit under the Law.

ROHM SEMICONDUCTOR

Thank you for your accessing to ROHM product informations.
More detail product informations and catalogs are available, please contact us.

ROHM Customer Support System

http://www.rohm.com/contact/