

### AM/FM/HD-Radio™/DAB automotive digital output tuner



#### **Features**



- AEC-Q100 qualified
- · Full automotive grade RFCMOS design
- · Quad-band:
  - AM/FM Band
  - Band-III
  - Band-L
- Two indipendent reception channels
- Integrated RF switch matrix in FM
- Software configurable digital base-band interface (I2S or JESD204B)
- Compatible with digital radio standards: DAB, DRM, and HD-Radio™
- · Software programmable
- Very high dynamic range built-in ΣΔ ADC
- Very low external component count (no pin diodes, transformers or varicap)
- · RoHS compliant small footprint package

### **Description**

The STA710 is a single chip, full CMOS, quad-band, dual channel front-end tuner specifically tailored to Software-Defined-Radio (SDR) systems.

When paired with an application processor, STA710 enables the implementation of a SDR solution to receive analog (AM/FM/WX) and digital terrestrial broadcasting standards (e.g. HD-Radio™/DAB/DRM).

The STA710 features front-end low-noise amplifiers (LNAs) covering AM band (LW/MW/SW), FM and WX bands, DAB band-III and band-L.

After on-chip IF filtering, the STA710 digitizes the signal with a high dynamic range  $\Sigma\Delta$  ADC ahead of the complex phase-quadrature base-band signal down conversion to provide a stable digital base-band output to the companion application processor.

The digital base-band signal is transmitted to the application processor via a flexible and configurable serial digital interface operating either as single-ended I2S, LVDS I2S or JESD204B.

The STA710 dual channel architecture enables a straightforward implementation of audio/data foreground-background reception strategies and multipath interference mitigation algorithms such as FM phase-diversity, DAB/DRM Maximal-Ratio-Combining (MRC) inside the companion application processor.

The STA710 offers automotive grade and state-of-art RF performances with minimum external component count.


### Product status link STA710

Product summary			
Order code	Package	Packing	
STA710EC	VFQFPN64	Tray	
STA710ECTR	(9x9x1 mm)	Tape & Reel	



# 1 Block diagram

Figure 1. Block diagram



DB3858 - Rev 2 page 2/7



# 2 Electrical specification

## 2.1 Absolute maximum ratings

Table 1. Absolute maximum ratings

Symbol	Parameter	Test condition	Min	Тур	Max	Units
V <sub>CC</sub>	Abs. supply voltage	-	-0.5	-	3.6	V
T <sub>stg</sub>	Storage temperature	-	-55	-	150	°C
		Human Body model	> ±2000  <sup>(1)</sup>			
$V_{ESD}$	V <sub>ESD</sub> ESD absolute minimum withstand voltage	Charged device model	> ±500  <sup>(2)</sup>		V	
		Charged device model, corner pins		> ±750	)	
-	Max. input current at any pin (latch-up characteristic)	I <sub>INMAX</sub>	±100		mA	

- 1. |±1000| on AM\_IN pin
- 2. |±400| on AM\_IN pin

#### 2.2 Thermal data

Table 2. Thermal data

Symbol	Parameter	Test Condition	Value	Units
R <sub>th j-amb</sub> Thermal Resistance junction-to-ambient	Multilayer 2s2p as per JEDEC JESD51-7	27 °C / W		
	Thermally optimized multilayer 2s2p board	22	C/W	

## 2.3 General key parameters

Table 3. General key parameters

Symbol	Parameter	Test Condition		Тур	Max	Units
V <sub>CC</sub>	3.3 V supply voltage		3.15	3.3	3.45	V
l	Cumply as mant	Two active RF channels,I2S baseband interface activated, $V_{CC}$ = 3.45 V	-	-	483	^
I <sub>CC</sub> Supply current	Two active RF channels, JESD204b interface activated (10 pF load), $V_{CC}$ = 3.45 V	-	-	504	- mA	
T <sub>amb</sub>	Ambient Temperature Range	-	-40	-	85	°C
T <sub>j_oper</sub>	Operative Junction Temp	-	-	-	125	°C
P <sub>diss</sub>	Dissipated power	Two active RF channels, R <sub>ext</sub> = 12 Ohm, I2S baseband interface activated	-	-	1.4	W
diss Dissipated power	Dissipated power	Two active RF channels, R <sub>ext</sub> = 12 Ohm, JESD204b interface activated	-	-	1.5	VV

DB3858 - Rev 2 page 3/7



## 3 Package information

In order to meet environmental requirements, ST offers these devices in different grades of ECOPACK packages, depending on their level of environmental compliance. ECOPACK specifications, grade definitions and product status are available at: www.st.com. ECOPACK is an ST trademark.

### 3.1 VFQFPN-64 (9x9x1.0mm) package information

Figure 2. VFQFPN-64 (9x9x1.0 mm) package outline




Table 4. VFQFPN-64 (9x9x1.0 mm) package mechanical data

Ref.	Dimensions in mm			
Nei.	Min.	Тур.	Max.	
Θ	-	-	14	
Α	-	-	1.0	
A1	0.00	-	0.05	
A2	0.55	-	0.80	
A3	0.20 REF			
b <sup>(1)</sup>	0.18	0.25	0.30	

DB3858 - Rev 2 page 4/7



Ref.		Dimensions in mm		
Ket.	Min.	Тур.	Max.	
b1	-	0.15	-	
D		9.00 BSC		
D1 <sup>(2)</sup>	8.75 BSC			
D2	-	6.70	-	
е		0.50 BSC		
E		9.00 BSC		
E1 <sup>(2)</sup>		8.75 BSC		
E2	-	6.70	-	
L	0.30	-	0.50	
L1	0.15 REF			
L2	-	0.10	-	
Р	-	-	0.60	
Tolerance of form and position	on			
aaa		0.15		
bbb		0.10		
ccc	0.10			
ddd	0.05			
eee		0.08		
fff	0.10			

<sup>1.</sup> Maximum allowable burr is 0.076 mm in all directions.

Note:

The package is compliant to IPC/JEDEC J-STD-020D June 2007 standard Moisture/Reflow Sensitivity Classification for Nonhermetic Solid State Surface Mount Devices, MSL Level 3.

DB3858 - Rev 2 page 5/7

<sup>2.</sup> D1 and E1 are Maximum plastic body size dimensions including mold mismatch. Dimensions D1 and E1 do not include mold flash or protrusions. Allowable mold flash or protrusions is "0.25 mm (0.0098 inch)" per side.



## **Revision history**

Table 5. Document revision history

Date	Version	Changes
26-Feb-2019	1	Initial release.
25-Nov-2019	2	Updated Figure 1. Block diagram.

DB3858 - Rev 2 page 6/7



#### **IMPORTANT NOTICE - PLEASE READ CAREFULLY**

STMicroelectronics NV and its subsidiaries ("ST") reserve the right to make changes, corrections, enhancements, modifications, and improvements to ST products and/or to this document at any time without notice. Purchasers should obtain the latest relevant information on ST products before placing orders. ST products are sold pursuant to ST's terms and conditions of sale in place at the time of order acknowledgement.

Purchasers are solely responsible for the choice, selection, and use of ST products and ST assumes no liability for application assistance or the design of Purchasers' products.

No license, express or implied, to any intellectual property right is granted by ST herein.

Resale of ST products with provisions different from the information set forth herein shall void any warranty granted by ST for such product.

ST and the ST logo are trademarks of ST. For additional information about ST trademarks, please refer to <a href="https://www.st.com/trademarks">www.st.com/trademarks</a>. All other product or service names are the property of their respective owners.

Information in this document supersedes and replaces information previously supplied in any prior versions of this document.

© 2019 STMicroelectronics - All rights reserved

DB3858 - Rev 2 page 7/7